

Compatibility Matrix

CommandCenter[®] Secure Gateway Release 6.1

Please review the Release Notes for important release information. Consult the Quick Setup, Deployment and Admin Guides at www.raritan.com/support/

It is important to upgrade any listed Raritan products to the specified versions indicated below.

CommandCenter Secure Gateway Firmware Information:

RARITAN PRODUCT	FIRMWARE VERSION	SHIPS WITH
CommandCenter Secure Gateway Physical and Virtual Appliances	6.1	Raritan Serial Console (RSC) 3.0.0

The CC-SG firmware version can be located under Help→About Raritan CommandCenter.
Firmware versions of all Raritan devices can be verified by running a CC-SG Device Asset Report.

CommandCenter Secure Gateway has been tested with the following Raritan product versions.

RARITAN PRODUCT & PART NUMBER		SUPPORTED FIRMWARE	
Product Name/Model	Part Number	Current	Previous
Dominion KX III	DKX3-108, DKX3-116, DKX3-132 DKX3-216, DKX3-232 DKX3-416, DKX3-432, DKX3-464 DKX3-808, DKX3-832, DKX3-864	3.2 ^{*6}	3.1.0
Dominion KX II	DKX2-108, DKX2-116, DKX2-132 DKX2-216, DKX2-232 DKX2-416, DKX2-432, DKX2-464 DKX2-808, DKX2-832, DKX2-864	2.7	2.6.0
Dominion KX II 101	DKX2-101, DKX2-101-v2	3.7 ^{*6}	2.0.40
Dominion SX II	DSX2-xxx, DSX2-xxxM	2.0 ^{*7}	N/A
Dominion SX (MIPS platform)	DSX4, DSX8, DSXA16, DSXA32, DSXA48	3.5	3.4.0
Dominion SX (Intel platform)	Older Intel-based models SX16 or SX32 ^{*2}	N/A	N/A
Dominion KSX II	DKSX2-144, DKSX2-188	2.7 ^{*6}	2.6.0
Dominion PX ^{*3}	DPCSxxx, DPCRxxx, DPXSxxx ^{*4}	1.5.13	1.5.8
Dominion PX2 ^{*5}	PX2-xxxx (managed through PowerIQ)	N/A	N/A
Dominion PX3	PX3-xxxx (managed through PowerIQ)	N/A	N/A
Power IQ	PWIQxxx	5.0.0	4.3.2
PCR Power Strips	PCR8, PCR12, PCR18, PCR20	N/A	N/A

Footnotes (above):

1. **The first generation Dominion KX models are not supported in CC-SG versions 6.0 or 6.1.**
2. The older SX Intel models (SX16 and SX32) are not supported. These models have serial numbers starting with WAA, WAB, SX, WP, or WQ. These two models also can be identified from the back panel by the absence of the RESET pin hole.
3. Dominion PX firmware versions listed in this Compatibility Matrix are required for direct connectivity to CC-SG via IP modes. For Dominion PX firmware versions required in 'managed power strip' mode (when Dominion PX connection to a Dominion device via a power CIM or power cable), refer to the documentation of the Dominion device managing the PX for special instructions.
4. xxx represents 3 alphanumeric values that would be different for each model in the product category.
5. PX2 and PX3 management requires the use of Raritan's Power IQ. Power IQ also supports many non-Raritan PDU's. Please refer to the Power IQ documentation for supported versions
6. Planned, future, supported versions scheduled for later in 2015
7. Dominion SX II Release 2.1 works with CC-SG Release 6.1, however the new, Java-free HTML Serial Client (HSC) does not; it will be supported by the future CC-SG 6.2 Release.

Third Party Applications & Interfaces:

THIRD PARTY PRODUCTS	SUPPORTED VERSIONS
VMware™ vSphere, ESXi	5.0.0, 5.1.0, 5.5.0
VMware ESX	5.0.0,5.1.0,5.5.0
VMware Remote Console	Version supported in VMware distribution
HP iLO4	2.03
HP iLO3	1.82
HP iLO2	2.27
HPiLO	1.94
HP Integrity iLO2	F.02.26
Apple iPad / iPhone	7.0, 8.0
Dell DRAC4	1.75
Dell DRAC5	1.60
Dell DRAC6	1.80
RSA II	1.14 (using Windows)
IBM IMM	1.x
IPMI	1.5, 2.0
Cisco UCS KVM	2.0
Telnet	1.0
RDP	1.1
Microsoft RDP	5.2.3790.0
VNC	2.7.2
SSH	1.0.1

The CC-SG Admin Client (Java) used by CC-SG administrators, and the CC-SG Access Client (HTML) used by end users, are supported in the following user desktop environments. Supported browsers are Microsoft Internet Explorer (IE) and Edge, Firefox (FF) and Chrome.

CLIENT PLATFORMS	SUPPORTED BROWSERS	SUN JRE ¹ SUPPORT
Windows 10	IE 11, FF 40, 41, Chrome 44, 45, Edge 20	1.8.0_60, 1.8.0_65
Windows 8 & 8.1	IE11, FF 35, 40, 41, Chrome 40, 44, 45	1.7.0_45, 1.7.0_80, 1.8.0_51, 1.8.0_60, 1.8.0_65
Windows 7	IE 10/11, Firefox 32-41, Chrome 37-45	1.7.0_67, 1.8.0_25, 1.8.0_51, 1.8.0_60, 1.8.0_65
Windows 2012 Server	Same as above	Same as above
SUSE 11	FF 16 through 20	Same as above
Solaris 10	FF 28	1.7.0_55
Fedora 16,18	FF 24, FF 26	1.7.0_45, 1.7.0_51, 1.8.0_60, 1.8.0_65
MacOS 10.8.5 Mountain Lion	Safari 6.1.1* ⁵ FF 25, FF 27	1.7.0_45, 1.7.0_51
MacOS X 10.9.5	Safari 7.1.8* ⁵ , Firefox 41, Chrome 43	1.7.0_45, 1.7.0_51 1.8.0_60, 1.8.0_65
Red Hat 6.4	Firefox 21	1.7.0_51

1. **CC-SG Release 6.1 has been tested with Java 8 up to 1.8.0_65 and Java 7 up to 7u80, which were the current versions at release time.**
2. **Future Java versions should work correctly assuming no incompatible changes are made by the Java developers. For any issues, please contact Tech Support who can provide workaround solutions or patch releases, if available.**
3. Chrome versions 45 (and above) and the Edge browser cannot launch in-band interfaces in the CC-SG HTML-based Access Client. If you plan to use the in-band interfaces, for best results, we recommend other browsers. If you must use these browsers for this purpose, then use the Java-based CC-SG Admin client to access your in-band interfaces, however iLO, DRAC and RSA will not launch.
4. Cannot login to CC-SG via IPv6 with Java 1.7.0.7_71. Previous versions work as does current Java 8 versions.
5. Unsupported Java versions include: 1.7.0_11 and 1.7 update 9-bo5. Sun JRE's can be found at <http://java.sun.com/j2se/>. **Java 6 is not supported by CC-SG 6.1.**
6. Both 32 and 64 bit OS editions are supported. If using Windows and using the client applet, JRE will only work with Windows 32 bit. See <http://java.sun.com/javase/6/webnotes/install/system-configurations.html> for Java support information.
7. Some platform-dependent issues can be resolved by using Firefox (FF) instead of Safari.

CLI access to CC-SG is supported in the following user desktop environments:

CLIENT APPLICATIONS	SUPPORTED VERSIONS
SSH	PuTTY version 0.58 or later. OpenSSH