

CommandCenter[®] Secure Gateway Release 6.2

Please review the Release Notes for important release information. Consult the Quick Setup, Deployment and Admin Guides at www.raritan.com/support/

It is important to upgrade any listed Raritan products to the specified versions indicated below.

CommandCenter Secure Gateway Firmware Version

RARITAN PRODUCT	FIRMWARE VERSION
CommandCenter Secure Gateway Physical and Virtual Appliances	6.2

CommandCenter Secure Gateway has been tested with the following Raritan product versions:

RARITAN PRODUCT & PART NUMBER		SUPPORTED FIRMWARE	
Product Name/Model	Part Number	Current	Previous
Dominion KX III	DKX3-108, DKX3-116, DKX3-132 DKX3-216, DKX3-232 DKX3-416, DKX3-432, DKX3-464 DKX3-808, DKX3-832, DKX3-864	3.4* ⁶	3.1.0
Dominion KX II	DKX2-108, DKX2-116, DKX2-132 DKX2-216, DKX2-232 DKX2-416, DKX2-432, DKX2-464 DKX2-808, DKX2-832, DKX2-864	2.7	2.6.0
Dominion KX II 101	DKX2-101, DKX2-101-v2	3.7	2.0.40
Dominion SX II	DSX2-xxx* ⁴ , DSX2-xxx* ⁴ M	2.2* ⁶	2.0
Dominion SX (MIPS platform)	DSX4, DSX8, DSXA16, DSXA32, DSXA48	3.5	3.4.0
Dominion SX (Intel platform)	Older Intel-based models SX16 or SX32 * ²	N/A	N/A
Dominion KSX II	DKSX2-144, DKSX2-188	2.7	2.6.0
Dominion PX* ³	DPCSxxx* ⁴ , DPCRxxx* ⁴ , DPXSxxx* ⁴	1.5.20	1.5.13
Dominion PX2* ³	PX2-xxxx* ⁴	3.2.10.5.42978	N/A
Dominion PX3* ³	PX3-xxxx* ⁴	3.2.10.5.42978	N/A
Power IQ	PWIQxxx* ⁴	5.1.3.4	5.0.0

The CC-SG firmware version can be located under Help→About Raritan CommandCenter.
Firmware versions of all Raritan devices can be verified by running a CC-SG Device Asset Report.

Footnotes (above):

1. The first generation Dominion KX models are **not supported in CC-SG versions 6.0, and later.**
2. The older SX Intel models (SX16 and SX32) are not supported. These models have serial numbers starting with WAA, WAB, SX, WP, or WQ. These two models also can be identified from the back panel by the absence of the RESET pin hole.
3. Dominion PX firmware versions listed in this Compatibility Matrix are for a direct connection to CC-SG via TCP/IP and SNMP. For Dominion PX firmware versions required in 'managed power strip' mode (when the PX is connected to a Dominion device), refer to the documentation of the Dominion device. For PDU's connected to Power IQ, please refer to the Power IQ documentation.
4. xxx represents 3 alphanumeric values that would be different for each model in the product category.
5. PX2 and PX3 management requires the use of Raritan's Power IQ. Power IQ also supports many non-Raritan PDU's.
6. Future, supported version tested with CC-SG.

Third Party Applications & Interfaces:

THIRD PARTY PRODUCTS	SUPPORTED VERSIONS
VMware™ vSphere, ESXi	5.0.0, 5.1.0, 5.5.0,6.0
VMware Remote Console	Version supported in VMware distribution
HP iLO4	2.44
HP iLO3	1.87
HP iLO2	2.29
HPiLO	1.94
HP Integrity ILO2	F.02.26
Apple iPad / iPhone	9.3.5
Dell DRAC4	1.75
Dell DRAC5	1.60
Dell DRAC6	2.80
Dell DRAC7	2.20.20.20
Dell DRAC8	2.21.21.21
RSA II	1.14 (using Windows)
IBM IMM	1.x
IPMI	1.5, 2.0
Cisco UCS KVM	2.2
Telnet	1.0
RDP	1.1
Microsoft RDP	5.2.3790.0
VNC	2.7.2
SSH	1.1.0

The CC-SG Admin Client (Java) used by CC-SG administrators, and the CC-SG Access Client (HTML) used by end users, are supported in the following user desktop environments. Supported browsers are Microsoft Internet Explorer (IE) and Edge, Firefox (FF), Chrome and Safari.

CLIENT PLATFORMS	SUPPORTED BROWSERS	SUN JRE ¹ SUPPORT
Windows 10	IE 11, FF 40, 41, Chrome 44, 45, Edge 20 FF 47, 48 and 49 Chrome 53, 54	1.8.0_60, 1.8.0_65 1.8.0_101, 1.8.0_111
Windows 8.1	IE11, FF 35, 40, 41, Chrome 40, 44, 45,53 and 54 FF 47,48 and 49	1.7.0_45, 1.7.0_80, 1.8.0_51, 1.8.0_60, 1.8.0_65 1.8.0_101
Windows 7	IE 10/11, Firefox 32-41, Chrome 37-45 FF 48 and 49 Chrome 53, 54	1.7.0_67, 1.8.0_25, 1.8.0_51, 1.8.0_60, 1.8.0_65 1.8.0_101, 1.8.0_111
Windows 2008	IE 11	1.8.0_101
Windows 2012 Server	IE 11	1.8.0_101
Solaris 11	FF 30	1.7.0_80
Fedora 22,24	FF 47, Chrome 52	1.8.0_101, 1.8.0_111
Mac 10.11.9	Safari 9.0, 9.1.2 FF 37.02, 49 Chrome 53,54	1.8.0_101
Mac OS Sierra 10.12	Safari 10.0	1.8.0_112-ea
Red Hat 7	FF 48	1.8.0_101
openSUSE 13.1	FF 49	1.8.0_111

Notes:

1. CC-SG Release 6.2 has been tested with Java 8 up to **1.8.0_112** and Java 7 up to **7u80**, which were the current versions at release time.
2. Future Java versions should work correctly assuming no incompatible changes are made. For issues, please contact Tech Support who can provide workaround solutions or patch releases, if available.
3. Chrome versions 45 (and above) and the Edge browser cannot launch in-band interfaces in the CC-SG HTML-based Access Client. If you plan to use the in-band interfaces, for best results, we recommend other browsers. If you must use these browsers for this purpose, then use the Java-based CC-SG Admin client to access your in-band interfaces, however iLO, DRAC and RSA will not launch.
4. Sun JRE's can be found at <http://java.sun.com/j2se/>. Java 6 is not supported by CC-SG 6.2.
5. Both 32 and 64 bit OS editions are supported. If using Windows and using the client applet, JRE will only work with Windows 32 bit. See <http://java.sun.com/javase/6/webnotes/install/system-configurations.html> for Java support information.
6. Some platform-dependent issues can be resolved by using Firefox (FF) instead of Safari.

CLI access to CC-SG via SSH is supported by PuTTY version 0.58 or later. Open SSH: